Research Repository UCD

Title	Fundamental Limits of Spectrum Sharing for NOMA-Based Cooperative Relaying
Authors(s)	Kumar, Vaibhav, Cardiff, Barry, Flanagan, Mark F.
Publication date	2018-12-13
Publication information	Kumar, Vaibhav, Barry Cardiff, and Mark F. Flanagan. "Fundamental Limits of Spectrum Sharing for NOMA-Based Cooperative Relaying." IEEE, 2018.
Conference details	2018 IEEE Globecom Workshops (GC Wkshps), Abu Dhabi, United Arab Emirates, 9-13 December 2018
Publisher	IEEE
Item record/more information	http://hdl.handle.net/10197/11112
Publisher's statement	© 2018 IEEE. Personal use of this material is permitted. Permission from IEEE must be obtained for all other uses, in any current or future media, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works, for resale or redistribution to servers or lists, or reuse of any copyrighted component of this work in other works.
Publisher's version (DOI)	10.1109/GLOCOMW.2018.8644252

Downloaded 2023-04-07T10:52:29Z

The UCD community has made this article openly available. Please share how this access benefits you. Your story matters! (@ucd_oa)

© Some rights reserved. For more information

Fundamental Limits of Spectrum Sharing for NOMA-based Cooperative Relaying

Vaibhav Kumar^{*}, Barry Cardiff[†], and Mark F. Flanagan[‡]

School of Electrical and Electronic Engineering, University College Dublin, Belfield, Dublin 4, Ireland

Email: ^{*}vaibhav.kumar@ucdconnect.ie, [†]barry.cardiff@ucd.ie, [‡]mark.flanagan@ieee.org

Abstract—Non-orthogonal multiple access (NOMA) and spectrum sharing (SS) are two emerging multiple access technologies for efficient spectrum utilization in the fifth-generation (5G) wireless communications standard. In this paper, we present a closed-form analysis of the average achievable sum-rate and outage probability for a NOMA-based cooperative relaying system (CRS) in an underlay spectrum sharing scenario. We consider a peak interference constraint, where the interference inflicted by the secondary (unlicensed) network on the primary-user (licensed) receiver (PU-Rx) should be less than a predetermined threshold. We show that the CRS-NOMA outperforms the CRS with conventional orthogonal multiple access (OMA) for large values of peak interference power at the PU-Rx.

I. INTRODUCTION

With the proliferation of wireless communication technologies, services and applications, one of the major challenges for the 5G communication standard is to support large-scale heterogeneous data traffic. NOMA has recently been recognized as a promising multiple access technology for 5G wireless networks as it can accommodate several users within the same orthogonal resource block (time, frequency and/or spreading code) via multiplexing them in the power domain at the transmitter side and using successive interference cancellation (SIC) at the receiver to remove messages intended for other users [1]. In the case of NOMA, users with poor channel conditions have a larger share of transmission power, unlike the conventional OMA where more power is allocated to users with strong channel conditions (also known as the water-filling strategy) [2].

Cognitive radio (CR) is another emerging technology intended to enhance the spectrum utilization efficiency in wireless systems via SS. There are three main SS paradigms: underlay, overlay and interweave [3]. In underlay SS, secondary-users (SUs) operate in a frequency band originally owned by a PU such that the interference caused by the SUs on the primary network is less than a predefined limit, often referred to as the *interference temperature*. Therefore, no limit is directly imposed on the power transmitted from a SU transmitter (SU-Tx); it is sufficient that the interference caused at the PU receiver (PU-Rx) is below the threshold. In a fading channel, the secondary network may take advantage of this fact by opportunistically transmitting at a high power level when the interference channel between SU-Tx and PU-Rx is in a deep fade.

The closed-form expression for the relation between the secondary channel capacity and the peak/average interference

inflicted on the primary user for different fading distributions were quantified in [4]. The interference from the PU transmitter (PU-Tx) to the SU receiver (SU-Rx), also termed as the primary-to-secondary interference, was not considered in [4] and hence the results derived give an upper-bound on the achievable rate for the secondary network. The average achievable rate for the SS system in the low-power regime considering the primary-to-secondary interference were studied in [5], for general fading channels where in addition to the interference constraint, a transmit power constraint was also imposed on the SU-Tx.

Different models of spectrum sharing NOMA networks including underlay NOMA, overlay NOMA and cognitive NOMA were discussed in [6] and it was shown that cooperative relaying can improve reception reliability. As such, cooperative spectrum sharing NOMA networks have lower outage probability compared to their non-cooperative counterparts. A novel secondary NOMA relay assisted spectrum sharing scheme was proposed in [7], where first the quality-of-service (QoS) of the PU was guaranteed using maximal-ratio combining (MRC) and then the sum-rate of the SUs was maximized. Another interesting application of NOMA for spatially multiplexed transmission using a cooperative relaying system (CRS-NOMA) to enhance the spectral efficiency was presented in [8], where the source was able to deliver two different symbols to the destination in two-time slots with the help of a relay (here Rayleigh fading was considered). The CRS-NOMA can be easily seen to be superior to the conventional OMA relaying system in which a single symbol is delivered to the destination in two time slots. A performance analysis of the CRS-NOMA in Rician fading was presented in [9].

In this paper, we present the achievable sum-rate and outage probability analysis of the CRS-NOMA in an underlay SS scenario, where the power transmitted from the SU-Tx and from the relay are constrained by placing a limit on the peak interference power received at the PU-Rx. For clarity of exposition, no other constraint on the transmit power is imposed. While in practice, the transmit power from the SU-Tx or the relay is limited by hardware capabilities and other health-related safety considerations, the rates derived in this paper serve as an upper-bound on the capacity of the CRS-NOMA based SS system under a peak interference power constraint.

II. SYSTEM MODEL

Consider the spectrum sharing CRS-NOMA shown in Fig. 1, which consists of a SU-Tx S , a relay R , a SU-Rx D and a PU-Rx P . The SU-Tx S is equipped with a single transmit antenna and the PU-Rx P is equipped with a single receive antenna. The relay R is equipped with N_r receive antennas and a single transmit antenna, while the SU-Rx D is equipped with N_d receive antennas. It is assumed that all the nodes are operating in half-duplex mode and all the wireless links are assumed to be independent and Rayleigh distributed. The channel coefficient between the SU-Tx and the i^{th} receive antenna of the relay ($1 \leq i \leq N_r$) is denoted by $h_{sr,i}$ and has a mean-square value Ω_{sr} for all i , while that between the SU-Tx and the j^{th} antenna of the SU-Rx ($1 \leq j \leq N_d$) is denoted by $h_{sd,j}$ and has a mean-square value Ω_{sd} for all j . The channel coefficient between the transmit antenna of the

Fig. 1: System model for CRS-NOMA with underlay spectrum sharing.

relay and the j^{th} antenna of the SU-Rx is denoted by $h_{rd,j}$ and has a mean-square value Ω_{rd} for all j . Moreover, the channel coefficient between the SU-Tx and the PU-Rx is denoted by h_{sp} and has a mean-square value Ω_{sp} , while that between the transmit antenna of the relay and the PU-Rx is denoted by h_{rp} and has a mean-square value Ω_{rp} . Furthermore, it is assumed that the channels between the SU-Tx and the SU-Rx are on average weaker than those between the SU-Tx and the relay, i.e., $\Omega_{sd} < \Omega_{sr}$.

In the CRS-NOMA scheme with spectrum sharing, the SU-Tx broadcasts $\sqrt{a_1 P_s(h_{sp})} s_1 + \sqrt{a_2 P_s(h_{sp})} s_2$ to both relay and SU-Rx, where s_1 and s_2 are the data-bearing constellation symbols which are multiplexed in the power domain ($\mathbb{E}\{|s_i|^2\} = 1$ for $i = 1, 2$). $P_s(h_{sp})$ is the power transmitted from the SU-Tx and in general is a mapping from the fading coefficient h_{sp} to the set of non-negative real numbers $\mathbb{R}_+$ such that the instantaneous interference at the PU-Rx does not exceed a predetermined value (interference temperature). Moreover, a_1 and a_2 are power weighting coefficients satisfying the constraints $a_1 + a_2 = 1$ and $a_1 > a_2$. After receiving the signal from the SU-Tx, the SU-Rx decodes symbol s_1 treating the interference from s_2 as additional noise, while the relay first decodes symbol s_1 and then applies SIC to decode

s_2 . In the second time slot, the SU-Tx remains silent and only the relay transmits its estimate of symbol s_2 , denoted as $\hat{s}_2$, to the SU-Rx with power $P_r(h_{rp})$ which in general is a mapping from the fading coefficient h_{rp} to $\mathbb{R}_+$ such that the instantaneous interference at the primary receiver does not exceed the predetermined threshold. In this manner, two different symbols are delivered to the secondary receiver in two time slots.

In contrast to this, in the conventional OMA with underlay spectrum sharing scheme, the SU-Tx broadcasts symbol s_1 with power $P_s(h_{sp})$ in the first time slot and the relay retransmits the resulting symbol estimate $\hat{s}_1$ to the SU-Rx with power $P_r(h_{rp})$ in the second time slot. The SU-Rx then combines both the copies of symbol s_1 and in this manner only a single symbol is delivered to the SU-Rx in two time slots.

III. PERFORMANCE ANALYSIS

In this section we present the achievable sum-rate and outage probability analysis of the CRS-NOMA with underlay spectrum sharing under peak interference constraint. We first analyze the simple case where $N_r = N_d = 1$ and then we generalize these results to the case when $N_r \geq 1$ and $N_d \geq 1$.

A. Scenario I: $N_r = N_d = 1$

In this case we denote the channel coefficients for the S - D , S - R , R - D , S - P and R - P links by h_{sd} , h_{sr} , h_{rd} , h_{sp} and h_{rp} respectively. The signals received at the relay, the SU-Rx and the PU-Rx in the first time slot are, respectively,

$$\begin{aligned} y_{sr} &= h_{sr} \left(\sqrt{a_1 P_s(h_{sp})} s_1 + \sqrt{a_2 P_s(h_{sp})} s_2 \right) + n_{sr}, \\ y_{sd} &= h_{sd} \left(\sqrt{a_1 P_s(h_{sp})} s_1 + \sqrt{a_2 P_s(h_{sp})} s_2 \right) + n_{sd}, \\ y_{sp} &= h_{sp} \left(\sqrt{a_1 P_s(h_{sp})} s_1 + \sqrt{a_2 P_s(h_{sp})} s_2 \right) + n_{sp}, \end{aligned}$$

where $n_i, i \in \{sr, sd, sp\}$ is complex additive white Gaussian noise (AWGN) with zero mean and unit variance. The received instantaneous signal-to-interference-plus-noise ratio (SINR) at the relay for decoding symbol s_1 and the received instantaneous signal-to-noise ratio (SNR) for decoding symbol s_2 (assuming the symbol s_1 is decoded correctly) are given by $\gamma_{sr}^{(1)} = \lambda_{sr} a_1 P_s(h_{sp}) / \{\lambda_{sr} a_2 P_s(h_{sp}) + 1\}$ and $\gamma_{sr}^{(2)} = \lambda_{sr} a_2 P_s(h_{sp})$ respectively, where $\lambda_{sr} = |h_{sr}|^2$. Similarly, the received instantaneous SINR at the SU-Rx for decoding of s_1 is given by $\gamma_{sd} = \lambda_{sd} a_1 P_s(h_{sp}) / \{\lambda_{sd} a_2 P_s(h_{sp}) + 1\}$, where $\lambda_{sd} = |h_{sd}|^2$.

In the next time slot, the relay transmits the decoded symbol $\hat{s}_2$ to the SU-Rx with power $P_r(h_{rp})$. The received signals at the SU-Rx and the PU-Rx are, respectively,

$$\begin{aligned} y_{rd} &= h_{rd} \sqrt{P_r(h_{rp})} \hat{s}_2 + n_{rd}, \\ y_{rp} &= h_{rp} \sqrt{P_r(h_{rp})} \hat{s}_2 + n_{rp}, \end{aligned}$$

where $n_j, j \in \{rd, rp\}$ is complex AWGN with zero mean and unit variance. The received SNR at the SU-Rx for decoding the

symbol s_2 is given by $\gamma_{rd} = \lambda_{rd}P_r(h_{rp})$, where $\lambda_{rd} = |h_{rd}|^2$. Since the symbol s_1 should be decoded correctly at the SU-Rx as well as at the relay for SIC, while satisfying the interference constraint at the PU-Rx, the average achievable rate for symbol s_1 is given by (c.f. [8, eqn. (8)], [4, eqn. (1), eqn. (22)])

$$\begin{aligned} \bar{C}_{s_1} &= \max_{P_s(h_{sp}) \geq 0} \int_{|h_{sp}|} \int_{|h_{sr}|} \int_{|h_{sd}|} 0.5 \log_2 \left(1 + \min\{\gamma_{sr}^{(1)}, \gamma_{sd}\} \right) \\ &\quad \times g_1(|h_{sp}|)g_2(|h_{sr}|)g_3(|h_{sd}|) d|h_{sp}| d|h_{sr}| d|h_{sd}|, \quad (1) \\ \text{s.t.} \quad &\lambda_{sp}P_s(h_{sp}) \leq Q, \quad (2) \end{aligned}$$

where Q is the peak interference power that the PU-Rx can tolerate from the secondary network, and where $g_1(|h_{sp}|)$, $g_2(|h_{sr}|)$ and $g_3(|h_{sd}|)$ denote the probability density functions (PDFs) of $|h_{sp}|$, $|h_{sr}|$ and $|h_{sd}|$ respectively. Assuming no other limitation on the power transmitted from the SU-Tx, the optimal transmit power $P_s^*(h_{sp})$ which maximizes¹ the achievable rate is given by Q/λ_{sp} . Hence, the average achievable rate for symbol s_1 is given by

$$\begin{aligned} \bar{C}_{s_1} &= 0.5 \int_{|h_{sp}|} \int_{|h_{sr}|} \int_{|h_{sd}|} \log_2 \left(1 + \frac{\frac{\min\{\lambda_{sr}, \lambda_{sd}\} Q a_1}{\lambda_{sp}}}{\frac{\min\{\lambda_{sr}, \lambda_{sd}\} Q a_2 + 1}{\lambda_{sp}}} \right) \\ &\quad \times g_1(|h_{sp}|)g_2(|h_{sr}|)g_3(|h_{sd}|) d|h_{sp}| d|h_{sr}| d|h_{sd}| \\ &= 0.5 \left[\int_0^\infty \log_2(1+Qx) f_X(x) dx - \int_0^\infty \log_2(1+Qa_2x) f_X(x) dx \right], \quad (3) \end{aligned}$$

where $X \triangleq \min\{\lambda_{sr}, \lambda_{sd}\}/\lambda_{sp}$.

Theorem 1. A closed-form expression for the average achievable rate for the symbol s_1 is obtained as

$$\bar{C}_{s_1} = 0.5 \left[\frac{Q \log_2 \left(\frac{Q}{\phi \Omega_{sp}} \right)}{Q - \phi \Omega_{sp}} - \frac{a_2 Q \log_2 \left(\frac{a_2 Q}{\phi \Omega_{sp}} \right)}{a_2 Q - \phi \Omega_{sp}} \right], \quad (4)$$

where $\phi = (1/\Omega_{sr}) + (1/\Omega_{sd})$.

Proof: See Appendix A.

Similarly, the average achievable rate for symbol s_2 is given by (c.f. [8, eqn. (9)], [4, eqn. (1), eqn. (22)])

$$\begin{aligned} \bar{C}_{s_2} &= \max_{\substack{P_s(h_{sp}) \geq 0 \\ P_r(h_{rp}) \geq 0}} \int_{|h_{sp}|} \int_{|h_{rp}|} \int_{|h_{sr}|} \int_{|h_{rd}|} 0.5 \log_2 \left(1 + \min\{\gamma_{sr}^{(2)}, \gamma_{rd}\} \right) \\ &\quad \times g_1(|h_{sp}|)g_2(|h_{sr}|)g_4(|h_{rp}|)g_5(|h_{rd}|) d|h_{sp}| d|h_{sr}| d|h_{rp}| \\ &\quad \times d|h_{rd}|, \quad (5) \\ \text{s.t.} \quad &\lambda_{sp}P_s(h_{sp}) \leq Q, \quad (6) \\ &\lambda_{rp}P_r(h_{rp}) \leq Q, \quad (7) \end{aligned}$$

where $g_4(|h_{rp}|)$ and $g_5(|h_{rd}|)$ denote the PDFs of $|h_{rp}|$ and $|h_{rd}|$ respectively. Assuming no other limitation on the power transmitted from the SU-Tx and the relay, the optimal transmit power levels $P_s^*(h_{sp})$ and $P_r^*(h_{rp})$ which maximize the achievable rate are given by Q/λ_{sp} and Q/λ_{rp} , respectively.

¹Here we refer to maximization of the achievable rate for a given pair of power allocation coefficients a_1 and a_2 . The achievable rate can be further maximized by optimizing the power allocation coefficients a_1 and a_2 for a given optimal transmit power level $P_s^*(h_{sp})$.

Therefore, the average achievable rate for symbol s_2 is given by

$$\begin{aligned} \bar{C}_{s_2} &= \int_{|h_{sp}|} \int_{|h_{rp}|} \int_{|h_{sr}|} \int_{|h_{rd}|} 0.5 \log_2 \left(1 + \min\left\{ \frac{\lambda_{sr} a_2}{\lambda_{sp}}, \frac{\lambda_{rd}}{\lambda_{rp}} \right\} Q \right) \\ &\quad \times g_1(|h_{sp}|)g_2(|h_{sr}|)g_4(|h_{rp}|)g_5(|h_{rd}|) d|h_{sp}| d|h_{sr}| \\ &\quad \times d|h_{rp}| d|h_{rd}| \\ &= 0.5 \int_0^\infty \log_2(1+Qx) f_Y(x) dx = \frac{1}{2} \log_2(e) Q \int_0^\infty \frac{1-F_Y(x)}{1+Qx} dx, \quad (8) \end{aligned}$$

where $Y \triangleq \min\{\lambda_{sr} a_2/\lambda_{sp}, \lambda_{rd}/\lambda_{rp}\}$.

Theorem 2. A closed-form expression for the average achievable rate for the symbol s_2 is given by (9), shown at the top of the next page.

Proof: See Appendix B.

Using (4) and (9), the average achievable sum-rate for the CRS-NOMA is given as

$$\bar{C}_{\text{sum}} = \bar{C}_{s_1} + \bar{C}_{s_2}. \quad (10)$$

For the case of CRS-OMA, the signals received at the relay, the SU-Rx and the PU-Rx in the first time slot are, respectively,

$$\begin{aligned} y_{sr,\text{OMA}} &= h_{sr} \sqrt{P_s(h_{sp})} s_1 + n_{sr}, \\ y_{sd,\text{OMA}} &= h_{sd} \sqrt{P_s(h_{sp})} s_1 + n_{sd}, \\ y_{sp,\text{OMA}} &= h_{sp} \sqrt{P_s(h_{sp})} s_1 + n_{sp}. \end{aligned}$$

In the second time slot, the relay transmits its estimate of s_1 , denoted by $\hat{s}_1$ to the SU-Rx. The signals received at the SU-Rx and the PU-Rx in the second time slot are respectively,

$$\begin{aligned} y_{rd,\text{OMA}} &= h_{rd} \sqrt{P_r(h_{rp})} \hat{s}_1 + n_{rd}, \\ y_{rp,\text{OMA}} &= h_{rp} \sqrt{P_r(h_{rp})} \hat{s}_1 + n_{rp}. \end{aligned}$$

Following the same peak interference constraint as in the case of NOMA, the average achievable rate for the CRS-OMA system is given as

$$\bar{C}_{\text{OMA}} = 0.5 \mathbb{E}_Z [\log_2(1 + QZ)], \quad (11)$$

where² $Z \triangleq \min\left\{ \frac{\lambda_{sr}}{\lambda_{sp}}, \frac{\lambda_{sd}}{\lambda_{sp}} + \frac{\lambda_{rd}}{\lambda_{rp}} \right\}$ and $E_{\mathcal{W}}[\cdot]$ denotes the expectation with respect to the random variable $\mathcal{W}$.

Outage probability for CRS-NOMA: We define $\mathcal{O}_1$ as the outage event for symbol s_1 , i.e., the event where either the relay or the SU-Rx fails to decode s_1 successfully. Hence the outage probability for symbol s_1 is given by

$$\begin{aligned} \Pr(\mathcal{O}_1) &= \Pr(C_{s_1} < R_1) = \Pr\left[\frac{1}{2} \log_2 \left(1 + \frac{a_1 Q X}{a_2 Q X + 1} \right) < R_1 \right] \\ &= \Pr(X < \Theta_1) = \int_0^{\Theta_1} \frac{\phi \Omega_{sp}}{(1 + \phi \Omega_{sp} x)^2} dx = \frac{\phi \Omega_{sp} \Theta_1}{1 + \phi \Omega_{sp} \Theta_1}, \quad (12) \end{aligned}$$

where C_{s_1} is the instantaneous achievable rate for symbol s_1 , R_1 is the target data rate for symbol s_1 , $\epsilon_1 = 2^{2R_1} - 1$ and

²Here we assume that the SU-Rx applies MRC on the two copies of s_1 .

$$\bar{C}_{s_2} = \frac{0.5 a_2 \Omega_{rd} \Omega_{sr} Q \left[\Omega_{rp} \Omega_{sp} \log_2 \left(\frac{a_2 \Omega_{rp} \Omega_{sr}}{\Omega_{rd} \Omega_{sp}} \right) + a_2 \Omega_{rp} \Omega_{sr} Q \log_2 \left(\frac{\Omega_{rd} Q}{\Omega_{rp}} \right) - \Omega_{rd} \Omega_{sp} Q \log_2 \left(\frac{a_2 \Omega_{sr} Q}{\Omega_{sp}} \right) \right]}{(\Omega_{rd} \Omega_{sp} - a_2 \Omega_{rp} \Omega_{sr})(\Omega_{rd} Q - \Omega_{rp})(\Omega_{sp} - a_2 \Omega_{sr} Q)}. \quad (9)$$

$\Theta_1 = \frac{\epsilon_1}{Q(a_1 - \epsilon_1 a_2)}$. The integration above is solved using (22) and [10, eqn. (3.194-1)]. The system design must ensure that $a_1 > \epsilon_1 a_2$, otherwise the outage probability for symbol s_1 will always be 1 as noted in [11]. Next, we define $\mathcal{O}_2$ as the outage event for symbol s_2 . This outage event can be decomposed as the union of the following disjoint events: (i) symbol s_1 cannot be successfully decoded at the relay; (ii) symbol s_1 is successfully decoded at the relay, but symbol s_2 cannot be successfully decoded at the relay; and (iii) both symbols are successfully decoded at the relay, but symbol s_2 cannot be successfully decoded at the SU-Rx. Therefore, the outage probability for the symbol s_2 may be expressed as

$$\Pr(\mathcal{O}_2) = \begin{cases} \Pr\left(\frac{\lambda_{sr}}{\lambda_{sp}} < \Theta_1\right) + \Pr\left(\frac{\lambda_{sr}}{\lambda_{sp}} \geq \Theta_1, \frac{\lambda_{sr}}{\lambda_{sp}} < \Theta_2\right) \\ + \Pr\left(\frac{\lambda_{sr}}{\lambda_{sp}} \geq \Theta_2, \frac{\lambda_{rd}}{\lambda_{rp}} < \frac{\epsilon_2}{Q}\right); \text{ if } \Theta_1 < \Theta_2 \\ \Pr\left(\frac{\lambda_{sr}}{\lambda_{sp}} < \Theta_1\right) + \Pr\left(\frac{\lambda_{sr}}{\lambda_{sp}} \geq \Theta_1, \frac{\lambda_{rd}}{\lambda_{rp}} < \frac{\epsilon_2}{Q}\right); \\ \text{otherwise} \end{cases}$$

$$= F_{\frac{\lambda_{sr}}{\lambda_{sp}}}(\Theta) + F_{\frac{\lambda_{rd}}{\lambda_{rp}}}\left(\frac{\epsilon_2}{Q}\right) - F_{\frac{\lambda_{sr}}{\lambda_{sp}}}(\Theta) F_{\frac{\lambda_{rd}}{\lambda_{rp}}}\left(\frac{\epsilon_2}{Q}\right), \quad (13)$$

where R_2 is the target data rate for symbol s_2 , $\epsilon_2 = 2^{2R_2} - 1$, $\Theta_2 = \frac{\epsilon_2}{a_2 Q}$ and $\Theta = \max(\Theta_1, \Theta_2)$.

B. Scenario II: $N_r \geq 1, N_d \geq 1$

In this subsection, we generalize the results obtained in the previous subsection for the case when $N_r \geq 1, N_d \geq 1$ and selection combining (SC), i.e., selection of the antenna with highest instantaneous SNR, is used for reception at both relay and SU-Rx. The received instantaneous SINR at the relay for decoding symbol s_1 and the instantaneous SNR for decoding symbol s_2 (assuming the symbol s_1 is decoded correctly) are given by $\gamma_{sr,SC}^{(1)} = \delta_{sr} a_1 P_s(h_{sp}) / \{\delta_{sr} a_2 P_s(h_{sp}) + 1\}$ and $\gamma_{sr,SC}^{(2)} = \delta_{sr} a_2 P_s(h_{sp})$, respectively, where $i^* = \arg\max_{1 \leq i \leq N_r} |h_{sr,i}|$ and $\delta_{sr} = |h_{sr,i^*}|^2$. Similarly, the received instantaneous SINR at the SU-Rx for decoding symbol s_1 is given by $\gamma_{sd,SC} = \delta_{sd} a_1 P_s(h_{sp}) / \{\delta_{sd} a_2 P_s(h_{sp}) + 1\}$, where $j^* = \arg\max_{1 \leq j \leq N_d} |h_{sd,j}|$ and $\delta_{sd} = |h_{sd,j^*}|^2$. In the next time slot, the received instantaneous SNR at the SU-Rx for decoding symbol s_2 is given by $\gamma_{rd,SC} = \delta_{rd} P_r(h_{rp})$, where $k^* = \arg\max_{1 \leq k \leq N_d} |h_{rd,k}|$ and $\delta_{rd} = |h_{rd,k^*}|^2$. Following similar arguments as in the previous subsection, the average achievable rate for symbol s_1 using SC is given by

$$\bar{C}_{s_1,SC} = 0.5 \int_0^\infty \log_2(1 + Qx) f_{\mathcal{X}}(x) dx - 0.5 \int_0^\infty \log_2(1 + Qa_2 x) f_{\mathcal{X}}(x) dx, \quad (14)$$

where $\mathcal{X} \triangleq \min\{\delta_{sr}, \delta_{sd}\} / \lambda_{sp}$.

Theorem 3. A closed form expression for the average achievable rate for symbol s_1 using SC is obtained as

$$\bar{C}_{s_1,SC} = 0.5 \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} (-1)^{k+j} \binom{N_r}{k} \binom{N_d}{j} \times \left[\frac{Q \log_2 \left(\frac{Q}{\xi_{k,j} \Omega_{sp}} \right)}{Q - \xi_{k,j} \Omega_{sp}} - \frac{a_2 Q \log_2 \left(\frac{a_2 Q}{\xi_{k,j} \Omega_{sp}} \right)}{a_2 Q - \xi_{k,j} \Omega_{sp}} \right], \quad (15)$$

where $\xi_{k,j} = (k/\Omega_{sr}) + (j/\Omega_{sd})$.

Proof: See Appendix C.

Similarly, the average achievable rate for symbol s_2 using SC is given by

$$\bar{C}_{s_2,SC} = 0.5 \int_0^\infty \log_2(1 + Qx) f_{\mathcal{Y}}(x) dx, \quad (16)$$

where $\mathcal{Y} \triangleq \min\{\delta_{sr} a_2 / \lambda_{sp}, \delta_{rd} / \lambda_{rp}\}$.

Theorem 4. A closed-form expression for the average achievable rate for symbol s_2 using SC is obtained as (17), shown at the top of the next page.

Proof: See Appendix D.

Using (15) and (17), the average achievable rate for the CRS-NOMA using SC is given by

$$\bar{C}_{\text{sum},SC} = \bar{C}_{s_1,SC} + \bar{C}_{s_2,SC}. \quad (18)$$

With some algebraic manipulations, it can be shown that for $N_r = N_d = 1$, (18) reduces to (10). For the case of CRS-OMA with SC, the average achievable rate is given as

$$\bar{C}_{\text{OMA},SC} = 0.5 \mathbb{E}_{\mathcal{Z}} [\log_2(1 + Q\mathcal{Z})], \quad (19)$$

where $\mathcal{Z} \triangleq \min\{\frac{\delta_{sr}}{\lambda_{sp}}, \frac{\delta_{sd}}{\lambda_{sp}} + \frac{\delta_{rd}}{\lambda_{rp}}\}$.

Outage probability for CRS-NOMA with SC: Similar to the previous subsection, we define $\mathcal{O}_1$ as the outage event for symbol s_1 . Hence the outage probability for symbol s_1 using SC is given by

$$\Pr(\mathcal{O}_1) = \Pr(C_{s_1,SC} < R_1) = \Pr(\mathcal{X} < \Theta_1) = \int_0^{\Theta_1} f_{\mathcal{X}}(x) dx = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} (-1)^{k+j} \binom{N_d}{j} \binom{N_r}{k} \frac{\xi_{k,j} \Omega_{sp} \Theta_1}{1 + \xi_{k,j} \Omega_{sp} \Theta_1}, \quad (20)$$

where $C_{s_1,SC}$ is the instantaneous achievable rate for symbol s_1 in the CRS-NOMA using SC. The integration above is solved using (27) and [10, eqn. (3.194-1)]. Next, we define $\mathcal{O}_2$ as the outage event for symbol s_2 using SC, similar to the previous subsection. Hence, the outage probability for symbol s_2 is given by

$$\Pr(\mathcal{O}_2) = F_{\frac{\delta_{sr}}{\lambda_{sp}}}(\Theta) + F_{\frac{\delta_{rd}}{\lambda_{rp}}}\left(\frac{\epsilon_2}{Q}\right) - F_{\frac{\delta_{sr}}{\lambda_{sp}}}(\Theta) F_{\frac{\delta_{rd}}{\lambda_{rp}}}\left(\frac{\epsilon_2}{Q}\right). \quad (21)$$

$$\bar{C}_{s_2, SC} = 0.5Q \left[\sum_{k=1}^{N_r} (-1)^{k-1} \binom{N_r}{k} \frac{a_2 \Omega_{sr} \log_2 \left(\frac{a_2 \Omega_{sr} Q}{k \Omega_{sp}} \right)}{a_2 \Omega_{sr} Q - k \Omega_{sp}} + \sum_{j=1}^{N_d} (-1)^{j-1} \binom{N_d}{j} \frac{\Omega_{rd} \log_2 \left(\frac{\Omega_{rd} Q}{j \Omega_{rp}} \right)}{\Omega_{rd} Q - j \Omega_{rp}} \right. \\ \left. + \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} (-1)^{k+j} \binom{N_r}{k} \binom{N_d}{j} \left\{ \frac{k \Omega_{rd}^2 \Omega_{sp} \log_2 \left(\frac{j \Omega_{rp}}{Q \Omega_{rd}} \right)}{(k \Omega_{rd} \Omega_{sp} - j a_2 \Omega_{rp} \Omega_{sr})(Q \Omega_{rd} - j \Omega_{rp})} + \frac{j a_2^2 \Omega_{rp} \Omega_{sr}^2 \log_2 \left(\frac{a_2 Q \Omega_{sr}}{k \Omega_{sp}} \right)}{(k \Omega_{rd} \Omega_{sp} - j a_2 \Omega_{rp} \Omega_{sr})(a_2 Q \Omega_{sr} - k \Omega_{sp})} \right\} \right]. \quad (17)$$

(a) Simple case: $N_r = N_d = 1$. (b) General case: $N_r \geq 1, N_d \geq 1$.

Fig. 2: Comparison of average achievable rate for CRS based SS.

IV. RESULTS AND DISCUSSION

In this section, we present the analytical and simulation³ results for the average achievable rate and outage probability for the spectrum sharing based cooperative relaying system. We consider a scenario where $\Omega_{sd} = 1, \Omega_{sr} = \Omega_{rd} = 10$ and $\Omega_{sp} = \Omega_{rp} = 5.5$. For all the NOMA systems, we consider $a_2 = 0.1, R_1 = R_2 = 1$ bps/Hz. Fig. 2a shows a comparison of the average achievable rate for the SS based CRS with $N_r = N_d = 1$. It is clear from the figure that for small values of Q , the SS based CRS-OMA gives higher achievable rate, but for higher values of Q , the CRS-NOMA based SS system outperforms its OMA counterpart and achieves higher spectral efficiency.

In Fig. 2b, the average achievable rate for SS based CRS with selection combining is shown for different values of N_r and N_d . It is interesting to note that with an increase in the number of receive antennas at the relay and at the SU-Rx, the threshold value Q at which the CRS-NOMA outperforms its OMA counterpart becomes lower. Also, the agreement between the analytical and simulation results in Fig. 2 confirms the correctness of our sum-rate analysis.

Fig. 3a and Fig. 3b show the outage probability for symbol s_1 and s_2 respectively against Q and as expected, the outage probability decreases as the number of receive antennas is increased at the relay and at the SU-Rx.

V. CONCLUSION

In this paper, we provided a comprehensive achievable sum-rate and outage probability analysis of a NOMA based

³We do not realize the actual scenario for simulation, but rather generate the random variables and then evaluate the average achievable rate.

(a) Symbol s_1 .

(b) Symbol s_2 .

Fig. 3: Outage probability for CRS-NOMA with SS.

cooperative relaying system with spectrum sharing considering a peak interference power constraint. We considered the scenario where the relay and the secondary receiver are equipped with multiple receive antennas and where both apply selection combining to combine the received signal. It was shown that for higher values of peak interference power Q , the spectrum sharing system based on CRS-NOMA outperforms the spectrum sharing system based on conventional CRS-OMA, achieving higher spectral efficiency. Our results indicate that significant capacity gains can be achieved when the interference channel between the secondary transmitter/relay to primary receiver is in deep fade.

ACKNOWLEDGMENT

This publication has emanated from research conducted with the financial support of Science Foundation Ireland (SFI) and is co-funded under the European Regional Development Fund under Grant Number 13/RC/2077.

APPENDIX A PROOF OF THEOREM 1

Since $|h_i|, i \in \{sr, sd, rd, sp, rp\}$ is Rayleigh distributed, the PDF and the cumulative distribution function (CDF) of $\lambda_i = |h_i|^2$ are, respectively, given by

$$f_{\lambda_i}(x) = \frac{1}{\Omega_i} \exp\left(-\frac{x}{\Omega_i}\right), F_{\lambda_i}(x) = 1 - \exp\left(-\frac{x}{\Omega_i}\right).$$

Therefore, the PDF of $\min\{\lambda_{sr}, \lambda_{sd}\}$ is given as⁴

$$f_{\min\{\lambda_{sr}, \lambda_{sd}\}}(x) = f_{\lambda_{sr}}(x)[1 - F_{\lambda_{sd}}(x)] + f_{\lambda_{sd}}(x)[1 - F_{\lambda_{sr}}(x)] = \phi \exp(-\phi x),$$

⁴Given two random variables $\mathcal{U}$ and $\mathcal{V}$ with PDFs $f_{\mathcal{U}}(x)$ and $f_{\mathcal{V}}(x)$ respectively, and CDFs $F_{\mathcal{U}}(x)$ and $F_{\mathcal{V}}(x)$ respectively, the PDF of $\mathcal{W} \triangleq \min\{\mathcal{U}, \mathcal{V}\}$ is given by $f_{\mathcal{W}}(x) = f_{\mathcal{U}}(x)[1 - F_{\mathcal{V}}(x)] + f_{\mathcal{V}}(x)[1 - F_{\mathcal{U}}(x)]$ and the CDF of $\mathcal{W}$ is given by $F_{\mathcal{W}}(x) = F_{\mathcal{U}}(x) + F_{\mathcal{V}}(x) - F_{\mathcal{U}}(x)F_{\mathcal{V}}(x)$.

where $\phi = (1/\Omega_{sr}) + (1/\Omega_{sd})$. Using a transformation of random variables, the PDF of $X = \min\{\lambda_{sr}, \lambda_{sd}\}/\lambda_{sp}$ is therefore given as

$$f_X(x) = \int_0^\infty y f_{\min\{\lambda_{sr}, \lambda_{sd}\}}(yx) f_{\lambda_{sp}}(y) dy \\ = \frac{\phi}{\Omega_{sp}} \int_0^\infty y \exp\left[-\left(\phi x + \frac{1}{\Omega_{sp}}\right)y\right] dy = \frac{\phi \Omega_{sp}}{(1 + \phi \Omega_{sp} x)^2}. \quad (22)$$

The integral above is solved using [10, eqn. (3.351-3)]. Using (22), the first integral in (3) can be solved as

$$I_1 \triangleq \log_2(e) \phi \Omega_{sp} \int_0^\infty \frac{\ln(1 + Qx) dx}{(1 + \phi \Omega_{sp} x)^2} = \frac{Q \log_2\left(\frac{Q}{\phi \Omega_{sp}}\right)}{Q - \phi \Omega_{sp}}. \quad (23)$$

The integration above is solved using [10, eqn. (4.291-17)]. Similarly, the second integral in (3) can be solved as

$$I_2 \triangleq \log_2(e) \phi \Omega_{sp} \int_0^\infty \frac{\ln(1 + a_2 Qx) dx}{(1 + \phi \Omega_{sp} x)^2} = \frac{a_2 Q \log_2\left(\frac{a_2 Q}{\phi \Omega_{sp}}\right)}{a_2 Q - \phi \Omega_{sp}}. \quad (24)$$

Hence, using (3), (23) and (24), the closed-form expression for the average achievable rate for symbol s_1 in CRS-NOMA reduces to (4); this completes the proof.

APPENDIX B PROOF OF THEOREM 2

Using a transformation of random variables, we have

$$f_{\lambda_{sr} a_2}(x) = \frac{1}{a_2} f_{\lambda_{sr}}\left(\frac{x}{a_2}\right) = \frac{1}{a_2 \Omega_{sr}} \exp\left(\frac{-x}{a_2 \Omega_{sr}}\right).$$

Hence,

$$f_{\lambda_{sr} a_2 / \lambda_{sp}}(x) = \int_0^\infty y f_{\lambda_{sr} a_2}(yx) f_{\lambda_{sp}}(y) dy \\ = \frac{1}{a_2 \Omega_{sr} \Omega_{sp}} \int_0^\infty y \exp\left[-\left(\frac{x}{a_2 \Omega_{sr}} + \frac{1}{\Omega_{sp}}\right)y\right] dy \\ = \frac{a_2 \Omega_{sr} \Omega_{sp}}{(a_2 \Omega_{sr} + \Omega_{sp} x)^2}, \quad (\text{using [10, 3.351-3]})$$

and

$$F_{\lambda_{sr} a_2 / \lambda_{sp}}(x) = \int_0^x f_{\lambda_{sr} a_2 / \lambda_{sp}}(t) dt = \frac{\Omega_{sp} x}{a_2 \Omega_{sr} + \Omega_{sp} x}.$$

The integration above is solved using [10, eqn. (3.194-1)]. Similarly,

$$f_{\lambda_{rd} / \lambda_{rp}}(x) = \frac{\Omega_{rd} \Omega_{rp}}{(\Omega_{rd} + \Omega_{rp} x)^2}, \quad F_{\lambda_{rd} / \lambda_{rp}}(x) = \frac{\Omega_{rp} x}{\Omega_{rd} + \Omega_{rp} x}.$$

Therefore, we have

$$1 - F_Y(x) = 1 - F_{\lambda_{sr} a_2 / \lambda_{sp}}(x) - F_{\lambda_{rd} / \lambda_{rp}}(x) + F_{\lambda_{rd} / \lambda_{rp}}(x) \\ \times F_{\lambda_{sr} a_2 / \lambda_{sp}}(x) = \frac{a_2 \Omega_{sr} \Omega_{rd}}{(a_2 \Omega_{sr} + \Omega_{sp} x)(\Omega_{rd} + \Omega_{rp} x)}. \quad (25)$$

Using (8) and (25), the average achievable rate for symbol s_2 is given as

$$\bar{C}_{s_2} = \lim_{\Lambda \rightarrow \infty} \int_0^\Lambda \frac{0.5 \log_2(e) Q a_2 \Omega_{sr} \Omega_{rd} dx}{(a_2 \Omega_{sr} + \Omega_{sp} x)(\Omega_{rd} + \Omega_{rp} x)(1 + Qx)}. \quad (26)$$

Solving the integral above using partial fractions, (26) reduces to (9); this completes the proof.

APPENDIX C PROOF OF THEOREM 3

The CDF and PDF of δ_{sr} are, respectively,

$$F_{\delta_{sr}}(x) = 1 - \sum_{k=1}^{N_r} (-1)^{k-1} \binom{N_r}{k} \exp\left(\frac{-kx}{\Omega_{sr}}\right), \\ f_{\delta_{sr}}(x) = \sum_{k=1}^{N_r} (-1)^{k-1} \binom{N_r}{k} \frac{k}{\Omega_{sr}} \exp\left(\frac{-kx}{\Omega_{sr}}\right).$$

The CDF and PDF of δ_{sd} can be obtained by replacing N_r by N_d and Ω_{sr} by Ω_{sd} in the corresponding equations above. The PDF of $\min\{\delta_{sr}, \delta_{sd}\}$ is given by

$$f_{\min\{\delta_{sr}, \delta_{sd}\}}(x) = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} (-1)^{k+j} \binom{N_r}{k} \binom{N_d}{j} \xi_{k,j} \exp(-\xi_{k,j} x),$$

where $\xi_{k,j} = (k/\Omega_{sr}) + (j/\Omega_{sd})$. The PDF of $\mathcal{X} = \min\{\delta_{sr}, \delta_{sd}\}/\lambda_{sp}$ is therefore given by

$$f_{\mathcal{X}}(x) = \int_0^\infty y f_{\min\{\delta_{sr}, \delta_{sd}\}}(yx) f_{\lambda_{sp}}(y) dy = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \\ \times \binom{N_d}{j} \frac{(-1)^{k+j} \xi_{k,j}}{\Omega_{sp}} \int_0^\infty y \exp\left[-\left(\xi_{k,j} x + \frac{1}{\Omega_{sp}}\right)y\right] dy \\ = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \binom{N_d}{j} \frac{(-1)^{k+j} \xi_{k,j}}{\Omega_{sp}} \left(\xi_{k,j} x + \frac{1}{\Omega_{sp}}\right)^{-2}. \quad (27)$$

The integral above is solved using [10, eqn. (3.351-3)]. Now, the first integral in (14) can be solved as

$$I_3 \triangleq \log_2(e) \int_0^\infty \ln(1 + Qx) f_{\mathcal{X}}(x) dx = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \binom{N_d}{j} \\ \times \frac{(-1)^{k+j} \xi_{k,j}}{\ln(2) \Omega_{sp}} \int_0^\infty \ln(1 + Qx) \left(\xi_{k,j} x + \frac{1}{\Omega_{sp}}\right)^{-2} dx \\ = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \binom{N_d}{j} \frac{(-1)^{k+j} Q}{Q - \xi_{k,j} \Omega_{sp}} \log_2\left(\frac{Q}{\xi_{k,j} \Omega_{sp}}\right). \quad (28)$$

The integration above is solved using [10, eqn. (4.291-17)]. Similarly, the second integral in (14) can be solved as

$$I_4 \triangleq \log_2(e) \int_0^\infty \ln(1 + Q a_2 x) f_{\mathcal{X}}(x) dx \\ = \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \binom{N_d}{j} \frac{(-1)^{k+j} a_2 Q}{a_2 Q - \xi_{k,j} \Omega_{sp}} \log_2\left(\frac{a_2 Q}{\xi_{k,j} \Omega_{sp}}\right). \quad (29)$$

Using (14), (28) and (29), the closed-form expression for the average achievable rate for symbol s_1 in the CRS-NOMA with SC reduces to (15); this completes the proof.

APPENDIX D PROOF OF THEOREM 4

Using a transformation of random variables, the PDF of $\delta_{sr} a_2$ is given as

$$f_{\delta_{sr} a_2}(x) = \frac{f_{\delta_{sr}}\left(\frac{x}{a_2}\right)}{a_2} = \sum_{k=1}^{N_r} \binom{N_r}{k} \frac{(-1)^{k-1} k}{a_2 \Omega_{sr}} \exp\left(\frac{-kx}{a_2 \Omega_{sr}}\right).$$

The PDF of $\delta_{sr}a_2/\lambda_{sp}$ is given by

$$\begin{aligned} f_{\delta_{sr}a_2/\lambda_{sp}}(x) &= \int_0^\infty y f_{\delta_{sr}a_2}(yx) f_{\lambda_{sp}}(y) dy \\ &= \sum_{k=1}^{N_r} \binom{N_r}{k} \frac{(-1)^{k-1} k}{a_2 \Omega_{sr} \Omega_{sp}} \int_0^\infty y \exp\left[-\left(\frac{kx}{a_2 \Omega_{sr}} + \frac{1}{\Omega_{sp}}\right) y\right] dy \\ &= \sum_{k=1}^{N_r} \binom{N_r}{k} \frac{(-1)^{k-1} k}{a_2 \Omega_{sr} \Omega_{sp}} \left(\frac{kx}{a_2 \Omega_{sr}} + \frac{1}{\Omega_{sp}}\right)^{-2}. \end{aligned}$$

The integration above is solved using [10, 3.351-3]. Using [10, eqn. (3.194-1)], the CDF of $\delta_{sr}a_2/\lambda_{sp}$ is given by

$$F_{\frac{\delta_{sr}a_2}{\lambda_{sp}}}(x) = \int_0^x f_{\frac{\delta_{sr}a_2}{\lambda_{sp}}}(t) dt = \sum_{k=1}^{N_r} \binom{N_r}{k} \frac{(-1)^{k-1} k \Omega_{sp} x}{a_2 \Omega_{sr} + k \Omega_{sp} x}.$$

Similarly,

$$\begin{aligned} f_{\delta_{rd}/\lambda_{rp}}(x) &= \sum_{j=1}^{N_d} \binom{N_d}{j} \frac{(-1)^{j-1} j}{(\Omega_{rd} + \Omega_{rp})} \left(\frac{jx}{\Omega_{rd}} + \frac{1}{\Omega_{rp}}\right)^{-2}, \\ F_{\delta_{rd}/\lambda_{rp}}(x) &= \sum_{j=1}^{N_d} \binom{N_d}{j} \frac{(-1)^{j-1} j \Omega_{rp} x}{\Omega_{rd} + j \Omega_{rp} x}. \end{aligned}$$

Therefore, for $\mathcal{Y} = \min\{\delta_{sr}a_2/\lambda_{sp}, \delta_{rd}/\lambda_{rp}\}$, we have

$$\begin{aligned} 1 - F_{\mathcal{Y}}(x) &= 1 - F_{\frac{\delta_{sr}a_2}{\lambda_{sp}}}(x) - F_{\frac{\delta_{rd}}{\lambda_{rp}}}(x) + F_{\frac{\delta_{sr}a_2}{\lambda_{sp}}}(x) F_{\frac{\delta_{rd}}{\lambda_{rp}}}(x) \\ &= 1 - \sum_{k=1}^{N_r} \binom{N_r}{k} \frac{(-1)^{k-1} k \Omega_{sp} x}{a_2 \Omega_{sr} + k \Omega_{sp} x} - \sum_{j=1}^{N_d} \binom{N_d}{j} \frac{(-1)^{j-1} j \Omega_{rp} x}{\Omega_{rd} + j \Omega_{rp} x} \\ &\quad + \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} \binom{N_r}{k} \binom{N_d}{j} \frac{(-1)^{k+j} k j \Omega_{sp} \Omega_{rp} x^2}{(a_2 \Omega_{sr} + k \Omega_{sp} x)(\Omega_{rd} + j \Omega_{rp} x)}. \quad (30) \end{aligned}$$

Using (16), the average achievable rate for symbol s_2 using SC is given as

$$\begin{aligned} \bar{C}_{s_2, SC} &= 0.5 \int_0^\infty \log_2(1 + Qx) f_{\mathcal{Y}}(x) dx \\ &= 0.5 \log_2(e) Q \int_0^\infty \frac{1 - F_{\mathcal{Y}}(x)}{1 + Qx} dx. \quad (31) \end{aligned}$$

Now we define the integral I_5 as

$$\begin{aligned} I_5 &\triangleq \int_0^\infty \frac{1}{1 + Qx} \left(\frac{k \Omega_{sp} x}{a_2 \Omega_{sr} + k \Omega_{sp} x} \right) dx \\ &= \int_0^\infty \frac{1}{1 + Qx} \left(1 - \frac{a_2 \Omega_{sr}}{a_2 \Omega_{sr} + k \Omega_{sp} x} \right) dx \\ &= \int_0^\infty \frac{1}{1 + Qx} dx - \lim_{\Lambda \rightarrow \infty} \int_0^\Lambda \frac{a_2 \Omega_{sr} dx}{(a_2 \Omega_{sr} + k \Omega_{sp} x)(1 + Qx)} \\ &= \int_0^\infty \frac{1}{1 + Qx} dx - \frac{a_2 \Omega_{sr}}{a_2 \Omega_{sr} Q - k \Omega_{sp}} \ln \left(\frac{a_2 \Omega_{sr} Q}{k \Omega_{sp}} \right). \quad (32) \end{aligned}$$

The integration above is solved using partial fractions. Similarly,

$$\begin{aligned} I_6 &\triangleq \int_0^\infty \frac{1}{1 + Qx} \left(\frac{j \Omega_{rp} x}{\Omega_{rd} + j \Omega_{rp} x} \right) dx \\ &= \int_0^\infty \frac{1}{1 + Qx} dx - \frac{\Omega_{rd}}{\Omega_{rd} Q - j \Omega_{rp}} \ln \left(\frac{\Omega_{rd} Q}{j \Omega_{rp}} \right), \quad (33) \end{aligned}$$

and

$$\begin{aligned} I_7 &\triangleq \int_0^\infty \frac{1}{1 + Qx} \left(\frac{k j \Omega_{sp} \Omega_{rp} x^2}{(a_2 \Omega_{sr} + k \Omega_{sp} x)(\Omega_{rd} + j \Omega_{rp} x)} \right) dx \\ &= \int_0^\infty \frac{1}{1 + Qx} \left[1 + \frac{k \Omega_{rd}^2 \Omega_{sp}}{(a_2 j \Omega_{rp} \Omega_{sr} - k \Omega_{rd} \Omega_{sp})(\Omega_{rd} + j \Omega_{rp} x)} \right. \\ &\quad \left. + \frac{a_2^2 j \Omega_{rp} \Omega_{sr}^2}{(k \Omega_{rd} \Omega_{sp} - a_2 j \Omega_{rp} \Omega_{sr})(a_2 \Omega_{sr} + k \Omega_{sp} x)} \right] dx \\ &= \int_0^\infty \frac{1}{1 + Qx} dx + \frac{k \Omega_{rd}^2 \Omega_{sp} \ln \left(\frac{j \Omega_{rp}}{\Omega_{rd} Q} \right)}{(k \Omega_{rd} \Omega_{sp} - a_2 j \Omega_{rp} \Omega_{sr})(\Omega_{rd} Q - j \Omega_{rp})} \\ &\quad + \frac{a_2^2 j \Omega_{rp} \Omega_{sr}^2 \ln \left(\frac{a_2 \Omega_{sr} Q}{k \Omega_{sp}} \right)}{(k \Omega_{rd} \Omega_{sp} - a_2 j \Omega_{rp} \Omega_{sr})(a_2 \Omega_{sr} Q - k \Omega_{sp})}. \quad (34) \end{aligned}$$

Moreover, we also have

$$\begin{aligned} &\left[1 - \sum_{k=1}^{N_r} (-1)^{k-1} \binom{N_r}{k} - \sum_{j=1}^{N_d} (-1)^{j-1} \binom{N_d}{j} \right. \\ &\quad \left. + \sum_{k=1}^{N_r} \sum_{j=1}^{N_d} (-1)^{k+j} \binom{N_r}{k} \binom{N_d}{j} \right] \int_0^\infty \frac{dx}{1 + Qx} = 0. \quad (35) \end{aligned}$$

Using (31) – (35), the closed-form expression for the average achievable rate of symbol s_2 in CRS-NOMA using SC reduces to (17); this completes the proof.

REFERENCES

- [1] Y. Liu, Z. Qin, M. ElKashlan, Z. Ding, A. Nallanathan, and L. Hanzo, "Nonorthogonal multiple access for 5g and beyond," *Proc. of the IEEE*, vol. 105, no. 12, pp. 2347–2381, Dec 2017.
- [2] Z. Ding, Y. Liu, J. Choi, Q. Sun, M. ElKashlan, C. L. I, and H. V. Poor, "Application of non-orthogonal multiple access in LTE and 5G networks," *IEEE Commun. Mag.*, vol. 55, no. 2, pp. 185–191, February 2017.
- [3] A. Goldsmith, S. A. Jafar, I. Maric, and S. Srinivasa, "Breaking spectrum gridlock with cognitive radios: An information theoretic perspective," *Proc. of the IEEE*, vol. 97, no. 5, pp. 894–914, May 2009.
- [4] A. Ghasemi and E. S. Sousa, "Fundamental limits of spectrum-sharing in fading environments," *IEEE Trans. Wireless Commun.*, vol. 6, no. 2, pp. 649–658, Feb 2007.
- [5] L. Sboui, Z. Rezki, and M. S. Alouini, "Achievable rate of spectrum sharing cognitive radio systems over fading channels at low-power regime," *IEEE Trans. Wireless Commun.*, vol. 13, no. 11, pp. 6461–6473, Nov 2014.
- [6] L. Lv, J. Chen, Q. Ni, Z. Ding, and H. Jiang, "Cognitive non-orthogonal multiple access with cooperative relaying: A new wireless frontier for 5G spectrum sharing," *IEEE Commun. Mag.*, vol. 56, no. 4, pp. 188–195, Apr 2018.
- [7] B. Chen, Y. Chen, Y. Chen, Y. Cao, N. Zhao, and Z. Ding, "A novel spectrum sharing scheme assisted by secondary NOMA relay," *IEEE Wireless Commun. Lett.*, to appear.
- [8] J. B. Kim and I. H. Lee, "Capacity analysis of cooperative relaying systems using non-orthogonal multiple access," *IEEE Commun. Lett.*, vol. 19, no. 11, pp. 1949–1952, Nov 2015.
- [9] R. Jiao, L. Dai, J. Zhang, R. MacKenzie, and M. Hao, "On the performance of NOMA-based cooperative relaying systems over Rician fading channels," *IEEE Trans. Veh. Technol.*, vol. 66, no. 12, pp. 11 409–11 413, Dec 2017.
- [10] A. Jeffrey and D. Zwillinger, *Table of Integrals, Series, and Products*, 7th ed. Elsevier Science, 2007.
- [11] Z. Ding, H. Dai, and H. V. Poor, "Relay selection for cooperative NOMA," *IEEE Wireless Commun. Lett.*, vol. 5, no. 4, pp. 416–419, Aug 2016.